


REV	ECO No.	REVISION	DR	CK	DATE
01	168005	RELEASE	J.O.		22 JULY 19
02	179924	J6 RECEIPT WAS A TRIPLE C13	J.O.		28 JAN 20

NOTES:

- RACK MOUNTED STEEL CHASSIS, BLACK MEDIUM TEXTURE
19.00" WIDTH STANDARD RACK MOUNTING
5.190" HEIGHT 3U
20.00" DEPTH
NOTE: CHASSIS SUPPORT BRACKETS OR SLIDES ARE REQUIRED
- INPUT: 120/208 VAC 3-PHASE WYE 45A 50/60HZ
CONNECTION AT TERMINAL BLOCKS UNDER REAR COVER
CONDUIT HOLE AT BOTTOM OF COVER IS 1.312 DIA
- OUTPUTS:
200-240 VAC 16A AT THREE NEMA L15-20 RECEPTACLES;
100-125 VAC 12A AT TWELVE SWITCHED IEC C13 RECEPTACLES;
100-125 VAC 12A AT THREE UNSWITCHED IEC C13 RECEPTACLES
45A MAX PER PHASE
- MONITORING: CURRENT, POWER AND ENERGY
METERING FOR INPUT PHASES
- CIRCUIT BREAKERS:
ONE 4-POLE 60A MAIN, UL LISTED;
THREE 3-POLE 20A, ONE FOR EACH L15-20 RECEPTACLE, UL RECOGNIZED
THREE 1-POLE 15A, ONE FOR EACH GROUP OF C13 RECEPTACLES, UL RECOGNIZED
ONE 1-POLE 15A RESETTABLE, FOR UNSWITCHED RECEPTACLES J6, UL RECOGNIZED
- INDICATOR LIGHTS: 7 GREEN
1 FOR MAIN POWER
6, ONE FOR EACH BREAKER
- FILTER: 60A RATED, COMMON MODE LINE TO GROUND,
DIFFERENTIAL MODE, LINE TO LINE
- SPIKE & SURGE PROTECTION: LINE TO LINE, LINE TO NEUTRAL
- REMOTE I/O SWITCHING CONNECTORS: 2 REMOTE, 1 SEQUENCE
MATES WITH AMP NO. 1-480305-0 CONNECTOR WITH AMP NO. 60620-1 PINS.



REMOTE START REQUIRES THREE CONDITIONS:
1) ROCKER SWITCH SET TO "ON"
2) MOMENTARY CONTACT BETWEEN PINS 1 & 3 ON REMOTE CONNECTOR
3) MAINTAINED CONTACT BETWEEN PINS 2 & 3 ON REMOTE CONNECTOR

REMOTE POWER OFF/EPO REQUIRES:
1) TURNING OFF ROCKER SWITCH OR
2) OPENING CONNECTION BETWEEN PINS 2 AND 3 OF REMOTE CONNECTOR

FOR START UP OF ADDITIONAL LATCHING UNITS:
CONNECT PINS 1 & 2 ON SEQUENCE PORT TO A
REMOTE PORT ON ANOTHER LATCHING UNIT.
DO NOT CONNECT TO A SEQUENCE PORT.

MTD: SECTION X POWERS WHEN UNIT IS STARTED;
FOUR SECONDS LATER SECTION Y IS POWERED;
FOUR SECONDS LATER SECTION Z IS POWERED;
FOUR SECONDS LATER THE SEQUENCE PORT ACTIVATES

