



SMART3000RXLTAA Estimated Runtime

UPS	Extended Battery Module	EBM QTY	CONNECTED EQUIPMENT LOAD IN WATTS																		
			150	300	400	500	600	700	800	900	1,000	1,200	1,400	1,600	1,800	2,000	2,200	2,400	2,600	3,000	
SMART3000RXLTA	Internal batteries	n/a	162	73	52	41	33	27	23	20	17	13	10	8	7	6	5	4	4	3	
SMART3000RXLTA	BP72VRM2U	1	603	273	197	152	123	103	88	77	68	54	45	38	33	29	26	23	21	17	
SMART3000RXLTA	BP72VRM2U	2	1,112	503	363	281	228	190	163	142	125	100	83	71	61	54	48	43	39	33	
SMART3000RXLTA	BP72VRM2U	3	1,663	753	543	420	341	285	244	212	187	150	125	106	92	81	72	64	58	49	
SMART3000RXLTA	BP72VRM2U	4	2,247	1,017	733	568	460	385	329	287	253	203	169	144	124	109	97	87	79	67	
All runtime values are shown in minutes.																					